

# How to configure the Nowa 360 without Internet

## Context

The Nowa 360 system can be configured to be installed locally without an Internet connection even if it is better to connect to the Internet.

It will be necessary to disable the verification of the connection to the server as well as to enter the date and time in the system.

If the system loses its AC power and the backup battery becomes empty (due to a prolonged power failure), the date and time must be reconfigured in the system to start working again.

## Via Wi-Fi Discovery mode

1. Please refer to the document named **"How to activate the Wi-Fi discovery mode to access parameters"** to connect to the system
2. Once signed in, press on the **"Menu"** button on the top right of your screen
3. Press on **"Settings"**
4. Once landed on the settings page, press on the dropdown list underneath **"Settings Selector"** and select **"Reporting and Notifications"**
5. Underneath **"Format"** of Channel #1 **"Central Station Primary"** set the format to **"Use as Backup"**
6. Press on the dropdown list underneath **"Settings Selector"** and select **"System"**
7. Set the time and date underneath section **"System Date and Time"**
8. The system will no more show errors related to **"date and time loss"** and **"Internet link fault"**